KERN CCS 1T-1U



Counting system to count the smallest parts in large quantities, maximum number of parts which can be displayed is 999,999



Category	
Brand	KERN
Product categoriy	Industrial scale
Product group	Counting system
Product family	CCS
Measuring System	
Reference scale - item number	CFS 6K0.1
Quantity scale - Item number	KFU 1500V20M
Construction type of the scale	Multi-range balance
Weighing system	Strain gauge
Reference scale - Weighing capacity [Max]	6 kg
Quantity scale - Weighing capacity [Max]	1500 kg
Reference scale - Readability [d]	100 mg
Quantity scale - Readability [d]	0,5 kg
Linearity	±
Reference scale - Linearity	200 mg
Quantity scale - Linearity	1 kg
Reproducibility	0,0002 kg
Reference scale - Reproducibility	100 mg
Quantity scale - Reproducibility	0,5 kg
Default unit	kg
Units	kg Ib
Adjustment options	Adjusting with external weight
Recommended adjusting weight	1500 kg (M1)
Stabilization time	2 s
Eccentric loading at 1/3 [Max]	0,0005 kg
Reference scale - Eccentric loading at 1/3 [Max]	500 mg

at 1/3 [Max]	1 kg
Loadcell type	aluminum Alloy IP64
Approval	
CE mark	1
Display	
Display type	LCD
Display backlight	20D
Display digit height	20 mm
	20 mm
Construction	
Dimensions weighing platform (W×D×H)	840×1190×90 mm
Material housing	plastic
Material weighing plate	coated metal
Dimensions weighing surface (W×D)	840×1190 mm
Cable length	1,5 m
Display device cable length	5 m
Material load cell(s)	aluminium
Levelling feet adjustable	\checkmark
Functions	
Number of keys for operation	20
Number of keys for operation Auto-off interval(s) in battery mode/rechargeable battery mode	20 selectable
Auto-off interval(s) in battery	
Auto-off interval(s) in battery mode/rechargeable battery mode	selectable
Auto-off interval(s) in battery mode/rechargeable battery mode PreTare function	selectable
Auto-off interval(s) in battery mode/rechargeable battery mode PreTare function Tare function	selectable manual (multi)
Auto-off interval(s) in battery mode/rechargeable battery mode PreTare function Tare function Counting function	selectable ✓ manual (multi)
Auto-off interval(s) in battery mode/rechargeable battery mode PreTare function Tare function Counting function Tolerance weighing	selectable manual (multi) acoustically
Auto-off interval(s) in battery mode/rechargeable battery mode PreTare function Tare function Counting function Tolerance weighing Tolerance weighing - type of signal	selectable ✓ manual (multi) ✓ acoustically visual
Auto-off interval(s) in battery mode/rechargeable battery mode PreTare function Tare function Counting function Tolerance weighing Tolerance weighing - type of signal Conversion function	selectable manual (multi) acoustically visual
Auto-off interval(s) in battery mode/rechargeable battery mode PreTare function Tare function Counting function Tolerance weighing Tolerance weighing - type of signal Conversion function Recipe/summing level	selectable ✓ manual (multi) ✓ acoustically visual ✓ Sum A
Auto-off interval(s) in battery mode/rechargeable battery mode PreTare function Tare function Counting function Tolerance weighing Tolerance weighing - type of signal Conversion function Recipe/summing level PLU - total	selectable manual (multi) acoustically visual Sum A 100
Auto-off interval(s) in battery mode/rechargeable battery mode PreTare function Tare function Counting function Tolerance weighing Tolerance weighing - type of signal Conversion function Recipe/summing level PLU - total Sum memory function	selectable manual (multi) acoustically visual Sum A 100
Auto-off interval(s) in battery mode/rechargeable battery mode PreTare function Tare function Counting function Tolerance weighing - type of signal Conversion function Recipe/summing level PLU - total Sum memory function Memory function	selectable manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi) Manual (multi
Auto-off interval(s) in battery mode/rechargeable battery mode PreTare function Tare function Counting function Tolerance weighing - type of signal Conversion function Recipe/summing level PLU - total Sum memory function Memory function Underfloor weighing	selectable ✓ manual (multi) ✓ acoustically visual ✓ Sum A 100 ✓ None
Auto-off interval(s) in battery mode/rechargeable battery mode PreTare function Tare function Counting function Tolerance weighing - type of signal Conversion function Recipe/summing level PLU - total Sum memory function Memory function Underfloor weighing Interfaces	selectable ✓ manual (multi) ✓ acoustically visual ✓ Sum A 100 ✓ Sum A 100 Mone RS-232 standard

Smallest piece weight when piece counting - laboratory conditions 100 mg

1

KERN CCS 1T-1U



Counting system to count the smallest parts in large quantities, maximum number of parts which can be displayed is 999,999

Smallest piece weight when piece counting - normal conditions	1 g
Counting reference weight can be entered	1
Reference quantity	n (any number of pieces)
Counting resolution (laboratory conditions)	15.000.000
Power Supply	
Input voltage power supply / power [Max]	220 V - 240 V AC, 50 Hz
Input voltage device / power [Max]	12 V, 500 mA
Plug-in power supply type	Power adapter
Supplied power supply	Power supply unit
Plug-in power supply / adapter for countries - included with the	EURO UK
delivery	US CH
	EURO
Plug-in power supply / adapter for	AUS
countries - optional	UK
	US CH
Rechargeable battery optional	Rchrg. battery optional
Rechargeable battery charging time	12 h
Rechargeable battery operating time - backlight on	70 h
Rechargeable battery operating time - backlight off	60 h
Battery / accumulator type	Pb
Environmental conditions	
Humity of environment [Min]	0 %
Humity of environment [Max]	80 %
Ambient temperature [Min]	0°C
Ambient temperature [Max]	40 °C
Storage temperature [Min]	-20 °C
Storage temperature [Max]	0° 00
Packing & Shipping	
Readability force [d] (N)	4 d
Dimensions packaging (W×D×H)	1355×510×450 mm
Net weight	46 kg
Shipping method	Freight
Net weight approx.	46 kg
Gross weight approx.	50 kg
Shipping weight	50 kg

Services (optional)

Article number for adjustment at the location of installation	abhängig von Auflösung/ Max depends on resolution and capacity
Article number for DAkkS calibration	962-130-128
Article number for certificate of conformity (verification)	969-517

Pictograms

STANDARD



4 DAYS

OPTION

••	DAkkS
ACCU	+3 DAYS